

## Datasheet

Art.No. R1.188.3580.0

Device for monitoring of safety-related circuits SNO 4083KM-A  
1,5s\_DC 24V

Base unit also for elevators EN 81-1/2 and heaters EN50156-1 single-channel or two-channel control, automatic or manual reset with monitoring, cross circuit monitoring, 3 enabling current paths, 1 signalling output, DC 24 V, screw-terminals pluggable



Art.No.	R1.188.3580.0
EAN	4049088070884
Order unit	1 pieces

## Approvals



## Technical data

### General

Function display	3 LED, green
Creepage distances and clearances between the circuits	EN 60664-1
Protection degree according to DIN EN 60529 (housing)	IP40
Protection degree according to DIN EN 60529 (terminals)	IP20
Ambient temperature min.	-25 °C
Ambient temperature max.	65 °C
Wire ranges screw terminals, fine-stranded / solid	1 x 0,14 mm <sup>2</sup> - 2,5 mm <sup>2</sup> / 2 x 0,14 mm <sup>2</sup> - 0,75 mm <sup>2</sup>
Wire ranges screw terminals, fine-stranded with ferrules	1 x 0,25 mm <sup>2</sup> - 2,5 mm <sup>2</sup> / 2 x 0,25 mm <sup>2</sup> - 0,5 mm <sup>2</sup>
Permissible torque min.	0.5 Nm
Permissible torque max.	0.6 Nm
Tightening moment	0.6 Nm
Wire range cage clamp terminals	2 x 0,25mm <sup>2</sup> - 1,5mm <sup>2</sup>
Weight	0.2 kg
Standards	EN ISO 13849-1;EN 62061;EN 81-1;EN 50156-1
Suited for safety functions	Yes
Category according to EN ISO 13849-1	4
Muting possible	No
Feedback circuit	Yes
Start contact	Yes
Performance level acc. to EN ISO 13849-1	e
Rail mounting possible	Yes

### Connection Data

Detachable clamps	Yes
-------------------	-----

Type of electric connection	Screw connection
-----------------------------	------------------

### Application

Model	Basic device
Suitable for monitoring of magnetic switches	Yes
Suitable for monitoring of proximity switches	Yes
Suitable for monitoring of emergency-stop circuits	Yes
Suitable for monitoring of optoelectronic protection equipment	Yes
Suitable for monitoring of position switches	Yes

### Output circuit

Enabling paths	3
Signaling paths	1
Contact material	Ag-alloy, gold-plated
Max. thermal current I <sub>th</sub> , enabling paths	6 A
Max. thermal current I <sub>th</sub> , signaling paths	2 A
Max. total current I <sub>2</sub> of all current path	25 A <sup>2</sup>
Application category AC-15 (NO)	Ue 230V, Ie 3A
Application category DC-13 (NO)	Ue 24V, Ie 5A
Short-circuit protection (NO), max. fuse insert	6 A class gG fuse, fuse integral
Mechanical life	10 <sup>7</sup> switching cycles

### Control circuit

Nominal output voltage DC	22.5 V
Input current (safety circuit / reset circuit)	25 mA
max. peak current (safety circuit / reset circuit)	100 mA
Response time t <sub>A1</sub>	250 ms
Response time t <sub>A2</sub>	250 ms
Min. switch-on time	60 ms
Recovery time t <sub>W</sub>	120 ms
Release time t <sub>R</sub>	20 ms
Synchronous time t <sub>S</sub>	1.5 s
Permissible test pulse time t <sub>TP</sub>	0.8 ms
max. resistivity, per channel	≤ (5 + (1,176 × U <sub>B</sub> / U <sub>N</sub> - 1) × 100) Ω
Type of switch function of the inputs	Normally open contact
Evaluation inputs	2-channel

### Supply circuit

Nominal voltage U <sub>N</sub>	DC 24 V
Rated consumption DC	1.6 W
Operating voltage min.	20.4 V
Operating voltage max.	28.8 V

### Dimensions

Depth	114 mm
Width	22.5 mm
Height	96.5 mm

### Classification

ECLASS 8.1	27371819: Device for monitoring of safety-related circuits
ETIM 5.0	EC001449: Device for monitoring of safety-related circuits

Drawings

A	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	M1	M2	M3	L	0	1	11	21	11																																																																																																																				
				<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th colspan="2">Teil-Nr. / Part No.</th> </tr> </thead> <tbody> <tr><td>R1-188.0460.0</td><td></td></tr> <tr><td>R1-188.0470.0</td><td></td></tr> <tr><td>R1-188.0480.0</td><td></td></tr> <tr><td>R1-188.0490.0</td><td></td></tr> <tr><td>R1-188.0500.1</td><td></td></tr> <tr><td>R1-188.0530.1</td><td></td></tr> <tr><td>R1-188.0590.0</td><td></td></tr> <tr><td>R1-188.0620.0</td><td></td></tr> <tr><td>R1-188.0640.0</td><td></td></tr> <tr><td>R1-188.0680.0</td><td></td></tr> <tr><td>R1-188.0690.0</td><td></td></tr> <tr><td>R1-188.0700.2</td><td></td></tr> <tr><td>R1-188.0720.2</td><td></td></tr> <tr><td>R1-188.0900.1</td><td></td></tr> <tr><td>R1-188.0910.1</td><td></td></tr> <tr><td>R1-188.0940.1</td><td></td></tr> <tr><td>R1-188.0950.1</td><td></td></tr> <tr><td>R1-188.0990.0</td><td></td></tr> <tr><td>R1-188.1000.0</td><td></td></tr> <tr><td>R1-188.1010.0</td><td></td></tr> <tr><td>R1-188.1050.0</td><td></td></tr> <tr><td>R1-188.1090.0</td><td></td></tr> <tr><td>R1-188.1070.0</td><td></td></tr> <tr><td>R1-188.1120.0</td><td></td></tr> <tr><td>R1-188.1280.0</td><td></td></tr> <tr><td>R1-188.1340.0</td><td></td></tr> <tr><td>R1-188.1440.0</td><td></td></tr> <tr><td>R1-188.1450.0</td><td></td></tr> <tr><td>R1-188.1460.0</td><td></td></tr> <tr><td>R1-188.1480.0</td><td></td></tr> <tr><td>R1-188.1810.0</td><td></td></tr> <tr><td>R1-188.1820.0</td><td></td></tr> <tr><td>R1-188.1830.0</td><td></td></tr> </tbody> </table>		Teil-Nr. / Part No.		R1-188.0460.0		R1-188.0470.0		R1-188.0480.0		R1-188.0490.0		R1-188.0500.1		R1-188.0530.1		R1-188.0590.0		R1-188.0620.0		R1-188.0640.0		R1-188.0680.0		R1-188.0690.0		R1-188.0700.2		R1-188.0720.2		R1-188.0900.1		R1-188.0910.1		R1-188.0940.1		R1-188.0950.1		R1-188.0990.0		R1-188.1000.0		R1-188.1010.0		R1-188.1050.0		R1-188.1090.0		R1-188.1070.0		R1-188.1120.0		R1-188.1280.0		R1-188.1340.0		R1-188.1440.0		R1-188.1450.0		R1-188.1460.0		R1-188.1480.0		R1-188.1810.0		R1-188.1820.0		R1-188.1830.0		<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th colspan="2">Teil-Nr. / Part No.</th> </tr> </thead> <tbody> <tr><td>R1-188.1840.0</td><td></td></tr> <tr><td>R1-188.1850.0</td><td></td></tr> <tr><td>R1-188.1900.0</td><td></td></tr> <tr><td>R1-188.1870.0</td><td></td></tr> <tr><td>R1-188.1880.0</td><td></td></tr> <tr><td>R1-188.1890.0</td><td></td></tr> <tr><td>R1-188.1910.0</td><td></td></tr> <tr><td>R1-188.1920.0</td><td></td></tr> <tr><td>R1-188.1930.0</td><td></td></tr> <tr><td>R1-188.3250.0</td><td></td></tr> <tr><td>R1-188.3290.0</td><td></td></tr> <tr><td>R1-188.3360.0</td><td></td></tr> <tr><td>R1-188.3480.0</td><td></td></tr> <tr><td>R1-188.3580.0</td><td></td></tr> <tr><td>R1-188.3590.0</td><td></td></tr> <tr><td>R1-188.3620.0</td><td></td></tr> <tr><td>R1-188.3640.0</td><td></td></tr> <tr><td>R1-188.3660.0</td><td></td></tr> <tr><td>R1-188.3710.0</td><td></td></tr> <tr><td>R1-188.3810.0</td><td></td></tr> <tr><td>R1-188.3830.0</td><td></td></tr> <tr><td>R1-188.3840.0</td><td></td></tr> <tr><td>R1-188.3910.0</td><td></td></tr> <tr><td>R1-188.3930.0</td><td></td></tr> <tr><td>R1-188.4020.0</td><td></td></tr> <tr><td>R1-188.4100.0</td><td></td></tr> <tr><td>R1-188.4110.0</td><td></td></tr> <tr><td>R1-188.4120.0</td><td></td></tr> <tr><td>81-030.0100.0</td><td></td></tr> <tr><td>81-030.0101.0</td><td></td></tr> <tr><td>81-030.0110.0</td><td></td></tr> <tr><td>81-030.0111.0</td><td></td></tr> </tbody> </table>		Teil-Nr. / Part No.		R1-188.1840.0		R1-188.1850.0		R1-188.1900.0		R1-188.1870.0		R1-188.1880.0		R1-188.1890.0		R1-188.1910.0		R1-188.1920.0		R1-188.1930.0		R1-188.3250.0		R1-188.3290.0		R1-188.3360.0		R1-188.3480.0		R1-188.3580.0		R1-188.3590.0		R1-188.3620.0		R1-188.3640.0		R1-188.3660.0		R1-188.3710.0		R1-188.3810.0		R1-188.3830.0		R1-188.3840.0		R1-188.3910.0		R1-188.3930.0		R1-188.4020.0		R1-188.4100.0		R1-188.4110.0		R1-188.4120.0		81-030.0100.0		81-030.0101.0		81-030.0110.0		81-030.0111.0		<p>Weitere Angaben siehe KATALOG oder eKatalog. Additional data see CATALOG or eCatalog.</p> <p>www.wieland-electric.com eshop.wieland-electric.com</p>		<p>ja/yes <input type="checkbox"/> Stoffwechsel- und Paketelektroden nach DIN 5020.010 ist einstellbar. Conformity with Wieland document WM 5020.010 e (list of prohibited / degradable hazardous substances) to be declassified</p> <p>Übersicht / Overview <input type="checkbox"/> CAD-Zeichnung, nicht anmodifizieren allowed / not to be modified <input type="checkbox"/> 3D-Modell / Model <input type="checkbox"/> 2D-Zeichnung / Drawing No. <input type="checkbox"/> Zeichnung / Drawing No. <input type="checkbox"/> Blatt / Sheet: <input type="checkbox"/></p> <p>Material / Material: 2014 Leg. 006 Name: K030000          Lagerort / Warehouse: 03.02.15          Datum / Date: 03.02.15          DWG / File: 030181_E01K.DWG          Druck / Print: 03.02.15          Type: T R1.188.0460.0 01K          Made in: Made in Germany          Beschriftung / Title: Maßstabzeichnung/dimension drawing          Standard / Standard: Standard / Standard: 22,5mm.          Gehäuse / Housing: Gehäuse / Housing: Standard housing and cover, overall with 22.5mm          Plug-in PCB terminal: plug-in pcb terminal</p>	
Teil-Nr. / Part No.																																																																																																																																																	
R1-188.0460.0																																																																																																																																																	
R1-188.0470.0																																																																																																																																																	
R1-188.0480.0																																																																																																																																																	
R1-188.0490.0																																																																																																																																																	
R1-188.0500.1																																																																																																																																																	
R1-188.0530.1																																																																																																																																																	
R1-188.0590.0																																																																																																																																																	
R1-188.0620.0																																																																																																																																																	
R1-188.0640.0																																																																																																																																																	
R1-188.0680.0																																																																																																																																																	
R1-188.0690.0																																																																																																																																																	
R1-188.0700.2																																																																																																																																																	
R1-188.0720.2																																																																																																																																																	
R1-188.0900.1																																																																																																																																																	
R1-188.0910.1																																																																																																																																																	
R1-188.0940.1																																																																																																																																																	
R1-188.0950.1																																																																																																																																																	
R1-188.0990.0																																																																																																																																																	
R1-188.1000.0																																																																																																																																																	
R1-188.1010.0																																																																																																																																																	
R1-188.1050.0																																																																																																																																																	
R1-188.1090.0																																																																																																																																																	
R1-188.1070.0																																																																																																																																																	
R1-188.1120.0																																																																																																																																																	
R1-188.1280.0																																																																																																																																																	
R1-188.1340.0																																																																																																																																																	
R1-188.1440.0																																																																																																																																																	
R1-188.1450.0																																																																																																																																																	
R1-188.1460.0																																																																																																																																																	
R1-188.1480.0																																																																																																																																																	
R1-188.1810.0																																																																																																																																																	
R1-188.1820.0																																																																																																																																																	
R1-188.1830.0																																																																																																																																																	
Teil-Nr. / Part No.																																																																																																																																																	
R1-188.1840.0																																																																																																																																																	
R1-188.1850.0																																																																																																																																																	
R1-188.1900.0																																																																																																																																																	
R1-188.1870.0																																																																																																																																																	
R1-188.1880.0																																																																																																																																																	
R1-188.1890.0																																																																																																																																																	
R1-188.1910.0																																																																																																																																																	
R1-188.1920.0																																																																																																																																																	
R1-188.1930.0																																																																																																																																																	
R1-188.3250.0																																																																																																																																																	
R1-188.3290.0																																																																																																																																																	
R1-188.3360.0																																																																																																																																																	
R1-188.3480.0																																																																																																																																																	
R1-188.3580.0																																																																																																																																																	
R1-188.3590.0																																																																																																																																																	
R1-188.3620.0																																																																																																																																																	
R1-188.3640.0																																																																																																																																																	
R1-188.3660.0																																																																																																																																																	
R1-188.3710.0																																																																																																																																																	
R1-188.3810.0																																																																																																																																																	
R1-188.3830.0																																																																																																																																																	
R1-188.3840.0																																																																																																																																																	
R1-188.3910.0																																																																																																																																																	
R1-188.3930.0																																																																																																																																																	
R1-188.4020.0																																																																																																																																																	
R1-188.4100.0																																																																																																																																																	
R1-188.4110.0																																																																																																																																																	
R1-188.4120.0																																																																																																																																																	
81-030.0100.0																																																																																																																																																	
81-030.0101.0																																																																																																																																																	
81-030.0110.0																																																																																																																																																	
81-030.0111.0																																																																																																																																																	

R1\_188\_0460\_01K\_3\_CADW3072\_Rostener 2016-04-22T11:27:40 1.000